# HT3500, HT5000

# **Thermally Conductive Gap Fillers**

## **BENEFITS AND FEATURES**

- High thermal performance
- low contact resistance
- Easily dispensable and reworkable
- High compressibility for low stress applications
- Reliable thermal performance
- No pump out and cracking risk



#### **OVERVIEW**

Honeywell HT one-part series Gap Filler provides an effective thermal properties and high conformability with its high compressibility. It is formulated to deliver high dispense rates for improved productivity, long-term reliability performance and easy reworkability. It is designed to minimize thermal resistance at interfaces, maintain excellent performance through reliability testing, and provide scalable application at a competitive cost.

### TYPICAL APPLICATIONS

- Consumer electronics
- Telecommunications equipment
- Automotive electronics
- Power supplies & semiconductors
- Memory & power modules
- Power electronics

Property	HT3500	HT5000	Test Method
Feature	Silicone-based	Silicone-based	-
	Pre-cured	Pre-cured	-
Color	Dark red	Grey	Visual
Specific Gravity	3.2	3.4	ASTM D792
Thermal Conductivity (W/m·K)	3.5	5.0	ASTM D5470
Thermal Impedance (°C·cm²/W)	<0.35	<0.25	ASTM D5470 at BLT
Minimum BLT(mm)	0.10	0.05	-
Dispense Rate (g/min)	>10	>10	90Psi, 30cc EFD syringe
Out Gassing (TML)	<0.5%	<0.5%	ASTM E595
Storage Condition	RT	RT	-
Shelf (month)	12	12	-

#### **Honeywell Electronic Materials**

USA: 1-509-252-2102 China: 400-840-2233 Germany: 49-5137-999-9199 Japan: 81-3-6730-7092 Korea: 82-2-3483-5076

Korea: 82-2-3483-5076 Singapore: 65-6580-3593 Taiwan: 886-3-6580300 ext.312

www.electronicmaterials.com

Although all statements and information contained herein are believed to be accurate and reliable, they are presented without guarantee or warranty of any kind, express or implied. Information provided herein does not relieve the user from the responsibility of carrying out its own tests and experiments, and the user assumes all risks and liability for use of the information and results obtained. Statements or suggestions concerning the use of materials and processes are made without representation or warranty that any such use is free of patent infringement and are not recommendations to infringe any patent. The user should not assume that all toxicity data and safety measures are indicated herein or that other measures may not be required.

DS 0.318Rev2

©2019 Honeywell International Inc.